



Neo Auxin

FORD AUX - AUXFRD20

**IPOD CONNECTION KIT
INSTRUCTION MANUAL**

NEO AUXIN **FORD**

The Neo Auxin for Ford vehicles with Can-Bus radios converts the port on the back of the radio to an RCA audio input. The Neo Auxin has a built in audio adjuster allowing you to match the audio level of the device you are connecting to the current levels of your AM/FM or CD player.

AUX INPUT

The Neo Auxin adapter comes equipped with an AUX input which is an RCA connector. This AUX input allows you to connect any audio device that has a headphone or RCA jack. You will need to use an RCA to headphone jack cable (not included).

COMPATIBILITY

The Neo Auxin connects into your stereo by connecting to the CD Changer port on the back of the radio. It will replace the factory CD Changer if equipped.

IMPORTANT INSTALLATION INSTRUCTIONS
PLEASE READ BEFORE INSTALLING

PACKAGE CONTENTS

Neo Auxin – Black Box
Ford cable – 20-pin

INSTALLATION STEPS

- Step 1:** Disconnect the negative battery terminal.
- Step 2:** Remove the radio.
- Step 3:** Unplug 20pin connector from radio if present.
- Step 4:** Plug the 20pin connector on the neo harness into the radio.
- Step 5:** Connect the BLACK / GREEN wire on the Neo cable to chassis ground.
- Step 6:** Locate the 12v constant power on the 16pin cable that you originally unplugged from the radio.
 - ⇒ Use a line tester to locate which wire is the 12v constant. (This will be the wire that is receiving power when the keys are out of the ignition)
 - ⇒ Connect the GRAY / VIOLET wire to a 12v constant source. Use a line tap or T-tap to connect the wire.
- Step 7:** Reconnect the 16pin connector to the radio
- Step 8:** Connect the vehicle cable to the matching plug on the Neo box.
- Step 9:** Connect the audio output of your auxiliary device to the AUX input jack on the Neo Auxin.
- Step 10:** Reconnect the negative battery terminal.
- Step 11:** Test to make sure everything is working before you reinstall the radio.
- Step 12:** Reinstall the radio back into the dash of the vehicle.

ACCESSING THE AUX INPUT

Press the CD button twice and it will access the Auxiliary device.

NOTICES, WARNINGS, AND WARRANTY

One Year Limited Warranty

The quality controls used in the manufacture of this product ensure your satisfaction. This warranty applies only to the original purchaser of this product from an authorized dealer. This warranty covers any supplied or manufactured parts of this product that, upon inspection by NEO CAR AUDIO authorized personnel, is found to have failed in normal use due to defects in material or workmanship. This warranty does not apply to installation expenses. Operating this unit under conditions other than those recommended or voltages other than the voltage indicated on the unit, or attempting to service or modify the unit, will render this WARRANTY VOID. Unless otherwise proscribed by law, NEO CAR AUDIO shall not be liable for any personal injury, property damage or any incidental or consequential damages of any kind (including water damage) resulting from malfunctions, defects, misuse, improper installation or alteration of this product.

All parts of this NEO CAR AUDIO product are guaranteed for a period of 1 year as follows:

Within the first 12 months from date of purchase, subject to the conditions above, NEO CAR AUDIO will repair or replace the product if it is defective in material or workmanship providing it is returned to NEO CAR AUDIO, with PROOF OF PURCHASE from an authorized dealer. If you have a problem with this product, please call or write to our Customer Service Dept.

All warranty repair must have a RMA number from our service department. Contact Neo Car Audio for further warranty repair info.

Warning:

1. This equipment may be reset by unintentional electrostatic discharge during operation. Exposure to direct sunlight or extreme heat may cause damage or malfunction.
2. Do not disassemble or alter the cable and interface box.
3. Make the connections correctly
4. Do not cut away the wire sheath and use the power for other equipments.
5. Do not install in locations which might hinder vehicle operation or create hazards for vehicle occupants.
6. Have the wiring and installation done by professionals.
7. Arrange wiring so it is not crimped or pinched.
8. Do not use this product for purposes other than stated for the vehicle.

Caution:

1. The ACC Switch Output Connector has 10mA drive capability only. You must use a relay if higher ACC power output is required.
2. Use of headphones while operating an automobile or moving vehicle is not recommended and is unlawful in some countries and areas.
3. Be careful and attentive on the road. Stop operation of the Neo iOn if you find it disruptive or distracting while driving. The driver of a motor vehicle should not operate the Neo iOn while driving.

FCC Class B Radio Frequency Interference Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of FCC rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

1. Reorient or relocate the receiving antenna.
2. Increase the separation between the equipment and receiver.
3. Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
4. Consult the dealer or an experienced radio/television technician for help.

Notice 1: The changes or modifications not expressly approved by the party responsible for compliance could void the user authority to operate the equipment.

Notice 2: Shielded interface cables, if any, must be used in order to comply with the emission limits.

Copyrights, warnings, and other information

The illustrations, technical information, data and descriptions contained in this publication are subject to change without notice. This publication, together with all information contained in it, and all intellectual property rights on this publication remain the property of NEO CAR AUDIO. The user may not pass this publication on to third parties. No liability will be accepted for any inaccuracies or omissions in this publication, although due care has been taken to make it as complete and accurate as possible

iPod, 3rd Generation, 4th Generation, Mini, Photo, U2, HP, Nano and Video are registered trade marks of Apple Computers, Inc.

Ford is a registered trade mark of Ford Motor Company.

Design and specifications are subject to change without notice.

Looking for a Car Connection Kit for another vehicle radio?

Visit www.neocaraudio.com for more info. 619-704-0690